ADERTECH

User Manual



4CH DIGITAL POWER AMPLIFIER

PAMP-4120V2 (4x120W)
PAMP-4240V2 (4x240W)
PAMP-4350V2 (4x350W)
PAMP-4500V2 (4x500W)

Thank you for choosing ADERTECH products

We have done everything possible to ensure that our equipment pleases our consumers. When solving any problems in the operation and connection of ADERTECH equipment, it is best to contact authorized companies and specialists who work with our equipment. Our equipment is intended for professional use, so you have professional skills in using such equipment. ADERTECH is a manufacturer of a wide range of multimedia solutions.

Safety Precautions



The lightning flash with arrowhead symbol, within an equilateral triangle, is intended to alert the user to the presence of uninsulated "dangerous voltage" within the product's enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons.



The exclamation point within an equilateral triangle is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the appliance.



CAUTION Indicates a potentially hazardous situation which, if mishandled, could result in moderate or minor personal injury, and/or property damage.

• Before installation or use, be sure to carefully read all the instructions in this section for correct and safe operation.
• Be sure to follow all the precautionary instructions in this section, which contain important warnings and/or cautions regarding safety.
• After reading, keep this manual handy for future reference.

• Do not cut, kink, otherwise damage nor modify the power supply cord. In addition, avoid using the power cord in close proximity to heaters, and never place heavy objects – including the unit itself -- on the power cord, as doing so may result in fire or electric shock.
• Be sure to replace the unit's terminal cover after connection completion. Because high voltage is applied to the speaker terminals, never touch these terminals to avoid electric shock.
• Be sure to ground to the safety ground (earth) terminal to avoid electric shock. Never ground to a gas pipe as a catastrophic disaster may result.
• Avoid installing or mounting the unit in unstable locations, such as on a rickety table or a slanted surface.
• Doing so may result in the unit falling down, causing personal injury and/or property damage.

When the Unit is in Use

Should the following irregularity be found during use, immediately switch off the power, disconnect the power supply plug from the AC outlet and contact your nearest dealer.

·If you detect smoke or a strange smell coming from the unit.
·If water or any metallic object gets into the unit.
·If the unit falls, or the unit case breaks.
·If the power supply cord is damaged (exposure of the core, disconnection, etc.)
·If it is malfunctioning (no tone sounds.)

To prevent a fire or electric shock, never open nor remove the unit case as there are high voltage components inside the unit. Refer all servicing to your nearest dealer.

Do not insert nor drop metallic objects or flammable materials in the ventilation slots of the unit's cover, as this may result in fire or electric shock.

When Installing the Unit

Never plug in nor remove the power supply plug with wet hands, as doing so may cause electric shock.

When unplugging the power supply cord, be sure to grasp the power supply plug; never pull on the cord itself. Operating the unit with a damaged power supply cord may cause a fire or electric shock.

When moving the unit, be sure to remove its power supply cord from the wall outlet. Moving the unit with the power cord connected to the outlet may cause damage to the power cord, resulting in fire or electric shock.

When removing the power cord, be sure to hold its plug to pull.

Do not block the ventilation slots in the unit's cover. Doing so may cause heat to build up inside the unit and result in fire.

Avoid installing the unit in humid or dusty locations, in locations exposed to the direct sunlight, near the heaters, or in locations generating sooty smoke or steam as doing otherwise, may result in fire or electric shock.

When the Unit is in Use

Do not place heavy objects on the unit as this may cause it to fall or break which may result in personal injury and/or property damage. In addition, the object itself may fall off and cause injury and/or damage.

Make sure that the volume control is set to minimum position before power is switched on. Loud noise produced at high volume when power is switched on can impair hearing.

Do not operate the unit for an extended period of time with the sound distorting. This is an indication of a malfunction, which in turn can cause heat to generate and result in a fire.

Contact your dealer as to the cleaning. If dust is allowed to accumulate in the unit over a long period of time, a fire or damage to the unit may result.

If dust accumulates on the power supply plug or in the wall AC outlet, a fire may result. Clean it periodically. In addition, insert the plug in the wall outlet securely.

Switch off the power and unplug the power supply plug from the AC outlet for safety purposes when cleaning or leaving the unit unused for 10 days or more. Doing otherwise may cause a fire or electric shock.

Descriptions & Features



This series of professional grade 4-channel amplifier can deliver output power (Watts) options that are 4x120W, 4x240W, 4x350W and 4x500W. Line 70/100-volt and low impedance 4 ohms(Ω) output loads are provided.
The front panel includes a power switch, LED indicator lights include Power, Signal, Clip and Protection. The back panel includes 2 channels of signal inputs with gain controls that can be used to increase or decrease input levels on both channels.
This rack-mountable commercial amplifier features Class D amplification technology that is extremely energy efficient but also capable of producing a powerful output signal for large, medium, or small audio systems such as restaurants, meeting halls, sports venues, and other spaces where multiple speakers are needed.

Standard 19" 2U rack-mounting housing
Built-in 4 channels of Class D amplifier
4 channels of 70/100-volt output load
4 channels of 4 ohms(Ω) output load
Equipped with 4 channels of audio inputs with gain control
Audio loop outputs that provide to additional amplifiers
LED indicator lights include Power, Signal, Clip and Protection
Protections of short circuit, overload, high temperature

Front Panel



1. Power switch: Switch off the amplifier before make connection
2. Power indicators: Lights blue when the power is switched on
3. Signal indicators: Lights green when signal is input
4. Clip indicators: Lights yellow when an output signal clips (distortion occurs)
Note: If clipping occurs turn the gain control down on the back of the amplifier

5. Protection indicators: Lights red when protection circuitry activated
6. Rack mounting holes
7. Ventilation panel (Air Vent): A filter is located inside the ventilation panel

Protection Operation List

Failure	Protection	Operation Indicator	Remedy	Recovery
Overcurrent due to overload	Current limiter activated when impedance drops below the specified value	Peak indicator lights	Remove overload	Connecting a correct load automatically restores normal operation
Short circuit	Current limiter activated. Load disconnected	Protection indicator lights	Check speakers and lines for short circuit	Turn off the power switch. Correct the load, then switch on the power
Rise in amplifier unit temperature (over 85 ℃)	Load disconnected	Load disconnected	Check the unit for correct ventilation and overload	Operation automatically returns normal when the temperature decreases

Rear Panel



1. **AC power inlet**: Connect the supplied power cord to this inlet
2. **CH3 speaker connectors**: Please refer to next page for more details
3. **CH4 signal input/output & control**: Please refer to next page for more details
4. **CH3 signal input/output & control**: Please refer to next page for more details
5. **CH2 signal input/output & control**: Please refer to next page for more details
6. **CH1 signal input/output & control**: Please refer to next page for more details
7. **CH1 speaker connectors**: Please refer to next page for more details
8. **CH4 speaker connectors**: Please refer to next page for more details
9. **Ventilation outlet**
10. **CH2 speaker connectors**: Please refer to page 7 & 8 for more details

Notes of Signal Input & Output:



LINK: Ground, Cold, Hot
These connectors send audio to the other channel or output to other components

INPUT: Ground, Cold, Hot
These connectors receive audio source signal

CAUTION !

When use BALANCED signal:
Please connect the Ground, Cold, Hot wiring separately

When use UNBALANCED signal:
Please make the Ground and Cold being connected together

Speaker connections



Important Notes
This amplifier has different loudspeakers outputs of 100V,70V and low impedance 4Ω. It's only possible to use one output at the same time, connecting more than one may damage internal parts of the amplifier. Each of 100V, 70V, 4Ω terminals must work with COM.

100V line output

This system is most often used for public address system. Only use 100 V line loudspeakers with transformers. All loudspeakers are wired in parallel, and the sum of their power must not exceed the rated output power of the amplifier. It is advisable not to load the amplifier at more than 70% of its rated output power when using music sources.



70V line output

This system is common in the USA, it operates on the same principles as 100 V line except that at rated output power the amplifier has 70V RMS on its output terminals.



4Ω low impedance output

This output allows connection of low impedance loudspeakers without transformers. When two or more loudspeakers are used ensure that they are wired in a way that total load impedance remains between 4Ω.



Specifications

Model	PAMP-4120V2	PAMP-4240V2	PAMP-4350V2	PAMP-4500V2
Rated Power	4x120W	4x240W	4x350W	4x500W
Digital power amplifier	D			
Output Mode	4-16 Ohms (Ω), 70V, 100V			
Input Terminal	Phoenix terminal			
Output Terminal	Phoenix terminal			
Input Sensitivity	10KΩ 0.775V (0dBV)			
Aux Output	0.775V (0dBV)			
Fre. Response	20Hz~20kHz (±3dB)			
THD	<0.1% at 1kHz, 1/3 rated power			
S/N	>105dB			
Damping coefficient	600			
Cooling	DC24V FAN (automatic speed regulating fan)			
Indicators	POWER, SIGNAL, CLIP, PROTECTION			
AC Fuse	8A	8A	10A	12A
Power Input	AC100-240V 50-60Hz			
Consumption	800W	1600W	1950W	2700W
Dimension	89 (H) × 483 (W) × 366 (D) mm			
Net Weight	11.5kg	14.5kg	15.5kg	16.5kg

Disclaimer

Information contained in this manual is subject to change without prior notice and does not represent a commitment on the part of the vendor. We shall not be liable for any loss or damages whatsoever arising from the use of information or any error contained in this manual.

It is recommended that all services and repairs on this product be carried out by us or its authorized dealer. This product must only be used for the purpose it was intended by the manufacturer and in conjunction with this operating manual.

We cannot accept any liability whatsoever for any loss or damages caused by service, maintenance, or repair by unauthorized personnel, or by use other than that intended by the manufacturer.

Warranty Information

ADERTECH warrants all units to be free from defects in workmanship and materials, under normal use and service, for a period of one (1) year from the date of purchasing from authorized reseller.

If a product does not work as it warranted during this period, ADERTECH will repair or replace the defective product or its part. Replacement products may be new or reconditioned.

Warranty ends if the product has been damaged due to abuse, misuse, neglect, accident, unusual physical or electrical stress, unauthorized modifications, tampering, alterations, or servicing other than by ADERTECH or its authorized centers, causes other than from ordinary use or failure to properly use the Product in the application for which said Product is intended.

All trademarks are the property of their respective owners. ADERTECH assumes no responsibility for any errors that may appear in this publication. Product, pricing and feature information contained herein is subject to change without notice.

© 2023 ADERTECH Co Ltd. ADERTECH logo and its associated visual identity are trademarks or registered trademarks of ADERTECH and/or subsidiaries.